

V3-Daughterboard-Version-C3-SB-5716-2A

CN3 USB - call for usage



J2

MAIN L	10	9	MAIN R
AUX L	8	7	AUX R
+DC In	6	5	+DC In
GND	4	3	GND
M1	2	1	+5.0 Volt Out

J1

Serial connection for debug and program, compatible with Dream 5000DBG-IF

1	+5.0 Volt Out	max. 10mA
2	MIDI In	Standard MIDI IN at 31.25kb/s, 3.3V or 5V TTL
3	Gnd	Ground
4	Gnd	Ground
5	+DC In	+9V/500 mA DC Power supply (min 7V, Max 12V)
6	+DC In	+9V/500 mA DC Power supply (min 7V, Max 12V)
7	AUX R	Audio out Aux Right channel, +7.4dB, 5Vpp Max
8	AUX L	Audio out Aux Le channel, +7.4dB, 5Vpp Max
9	MAIN R	Audio out Main Right channel, +7.4dB, 5Vpp Max
10	MAIN L	Audio out Main Le channel, +7.4dB, 5Vpp Max